

CEL-FI™ QUATRA RED

Remote Annunciator Panel

ERRCS Solution

DATA SHEET

MODEL NUMBER:
F42-10R-100



Remote Annunciator Panel

The Cel-Fi QUATRA RED Remote Annunciator Panel provides automatic supervisory signals for malfunctions of the ERRCS solution. Rated NEMA 4, it complies with Chapter 10 of NFPA 72 and section 9.6.13 of NFPA 1221. The PoE architecture allows for a quick installation and alarm configuration. The unit includes a FORM-C cable compatible with any fire alarm control panel (open or short circuits)

Key Features

- Supports automatic supervisory signals for malfunctions of the ERRCS
- Complies with NFPA 72 and NFPA 1221
- Provides real-time system status
- NEMA-4 enclosure
- Small form factor

Use Cel-Fi WAVE PRO mobile app for seamless integration and configuration of the Cel-Fi QUATRA RED product line.



Benefits Intuitive interconnection with the fire alarm control panel
Doesn't require additional batteries to operate
Simple alarm set up using the WAVE PRO app

Network Unit Physical Specifications

	WIDTH		LENGTH		HEIGHT	
Dimensions	230 mm	9 in	230 mm	9 in	115 mm	4.5 in
Power	PoE					
Connectivity	RJ45					



Certifications

UL2524

FCC part 15

Supported Alarms

- Normal AC power
- Battery Charger Fail
- Donor antenna disconnection
- System component malfunction
- Loss of normal AC power
- Low Battery Capacity @ 30% of capacity
- Active RF emitting device malfunction
- Donor antenna malfunction

Copyright © 2020 by Nextivity, Inc, U.S. All rights reserved. The Nextivity and Cel-Fi logos are registered trademarks of Nextivity Inc. All other trademarks or registered trademarks listed belong to their respective owners. Designed by Nextivity in California. data_quatra-red-ra_eng_20-0427